

canalettoMDi Operation

System Overview

The canalettoMDi will auto detect whether the incoming video is SDI or HDI and switch into the appropriate mode. The LED on the front panel of the unit will illuminate orange during transition and will be solid green when stable.

To check which mode the unit is in press the 'info' button on the front panel and the LED will flash green....

If the unit is in HD mode (1080 or 720p) then the top left display will show CAHD.

If the unit is in SD mode (PAL or NTSC) then the top left display will show CASD.

....to return from this mode press the 'info' button again and the LED will illuminate solid green.

The unit has separate memories for HD and SD. The correct set of memories will be selected dependant on the incoming video.

Use the relevant attached user manual depending whether the mode is HD or SD.